



# IECEX Certificate of Conformity

## INTERNATIONAL ELECTROTECHNICAL COMMISSION IEC Certification System for Explosive Atmospheres

for rules and details of the IECEx Scheme visit [www.iecex.com](http://www.iecex.com)

Certificate No.: **IECEX BVS 23.0025X** Page 1 of 4 [Certificate history:](#)  
Issue No: 1 [Issue 0 \(2024-06-28\)](#)

Status: **Current**

Date of Issue: 2026-01-20

Applicant: **TURCK GmbH**  
Witzlebenstraße 7  
Mülheim an der Ruhr 45472  
Germany

Equipment: **Media converters type FOCEN11Ex-2G und FOCEN11-3G**

Optional accessory:

Type of Protection: **Intrinsic Safety "i", Encapsulation "m", Optical Radiation "op is", Increased Safety "e"**

Marking: **FOCEN11Ex-2G**  
Ex eb mb ib [ia Ga] [op is Ga] IIC T4 Gb  
[Ex ia Da] [Ex op is Da] IIIC

**FOCEN11-3G**  
Ex ec mc [op is Ga] IIC T4 Gc  
[Ex op is Da] IIIC

Approved for issue on behalf of the IECEx  
Certification Body:

**Deniz Pezzutto**

Position:

**Certification Manager**

Signature:  
(for printed version)

Date:  
(for printed version)

1. This certificate and schedule may only be reproduced in full.
2. This certificate is not transferable and remains the property of the issuing body.
3. The Status and authenticity of this certificate may be verified by visiting [www.iecex.com](http://www.iecex.com) or use of this QR Code.



Certificate issued by:

**DEKRA Testing and Certification GmbH**  
Certification Body  
Dinnendahlstrasse 9  
44809 Bochum  
Germany





# IECEx Certificate of Conformity

Certificate No.: **IECEx BVS 23.0025X**

Page 2 of 4

Date of issue: 2026-01-20

Issue No: 1

Manufacturer: **TURCK GmbH**  
Witzlebenstraße 7  
Mülheim an der Ruhr 45472  
Germany

Manufacturing  
locations: **TURCK GmbH**  
Witzlebenstraße 7  
Mülheim an der Ruhr 45472  
Germany

**Werner TURCK GmbH & Co. KG**  
Goethestraße 7  
58553 Halver  
Germany

This certificate is issued as verification that a sample(s), representative of production, was assessed and tested and found to comply with the IEC Standard list below and that the manufacturer's quality system, relating to the Ex products covered by this certificate, was assessed and found to comply with the IECEx Quality system requirements. This certificate is granted subject to the conditions as set out in IECEx Scheme Rules, IECEx 02 and Operational Documents as amended

## STANDARDS :

The equipment and any acceptable variations to it specified in the schedule of this certificate and the identified documents, was found to comply with the following standards

[IEC 60079-0:2017](#) Explosive atmospheres - Part 0: Equipment - General requirements  
Edition:7.0

[IEC 60079-11:2023](#) Explosive atmospheres - Part 11: Equipment protection by intrinsic safety "i"  
Edition:7.0

[IEC 60079-18:2017](#) Explosive atmospheres - Part 18: Protection by encapsulation "m"  
Edition:4.1

[IEC 60079-28:2015](#) Explosive atmospheres - Part 28: Protection of equipment and transmission systems using optical radiation  
Edition:2

[IEC 60079-7:2017](#) Explosive atmospheres - Part 7: Equipment protection by increased safety "e"  
Edition:5.1

This Certificate **does not** indicate compliance with safety and performance requirements other than those expressly included in the Standards listed above.

## TEST & ASSESSMENT REPORTS:

A sample(s) of the equipment listed has successfully met the examination and test requirements as recorded in:

Test Report:

[DE/BVS/ExTR24.0016/01](#)

Quality Assessment Report:

[DE/PTB/QAR06.0013/11](#)



# IECEX Certificate of Conformity

Certificate No.: **IECEX BVS 23.0025X**

Page 3 of 4

Date of issue: 2026-01-20

Issue No: 1

## EQUIPMENT:

Equipment and systems covered by this Certificate are as follows:

### Subject and Type

FOCEN11Ex-2G and FOCEN11-3G

### Description of the equipment

#### FOCEN11Ex-2G media converter:

The media converter type FOCEN11Ex-2G has an intrinsically safe (ia) Ethernet interface (IS-100BASE-TX) and an intrinsically interface (transmitter and receiver).

The media converter type FOCEN11Ex-2G converts signals from an intrinsically safe Ethernet interface (IS-100BASE-TX) into intrinsically safe optical signals or signals from the intrinsically safe optical interface (op is) into signals for the intrinsically safe Ethernet interface. The Ethernet circuits may be laid up to Zone 0 for gas applications and up to Zone 20 for dust applications. Light may be emitted up to Zone 0 for gas applications and up to Zone 20 for dust applications.

If the fiber optic cable is connected to a FOCEN11-3G, these two devices are also used to convert non-intrinsically safe Ethernet signals to intrinsically safe Ethernet signals.

#### FOCEN11-3G media converter

The media converter type FOCEN11-3G has an Ethernet interface and an intrinsically safe optical interface (transmitter and receiver).

The media converter type FOCEN11-3G converts signals from an Ethernet interface into intrinsically safe optical signals or signals from the intrinsically safe optical interface into signals for the Ethernet interface. Light may be emitted up to Zone 0 for gas applications and up to Zone 20 for dust applications.

If the fiber optic cable is connected to a FOCEN11Ex-2G, these two devices are also used to convert non-intrinsically safe Ethernet signals to intrinsically safe Ethernet signals.

#### For both types

For Group III applications, the FOCEN11Ex-2G and FOCEN11-3G media converters are associated equipment for use outside potentially explosive atmospheres without additional measures. The Ethernet circuits are electrically isolated from the supply lines.

### Listing of all components used referring to older standards

The media converters include no components.

### Parameters

See Annex

### SPECIFIC CONDITIONS OF USE: YES as shown below:

For use in potentially explosive gas atmospheres:

The FOCEN11Ex-2G and FOCEN11-3G media converters must be installed in an enclosure that has at least IP54 in accordance with IEC 60079-0.



# IECEx Certificate of Conformity

Certificate No.: **IECEx BVS 23.0025X**

Page 4 of 4

Date of issue: 2026-01-20

Issue No: 1

**DETAILS OF CERTIFICATE CHANGES (for issues 1 and above)**

Increase in maximum cable inductance from 0.4 mH/km to 1.4 mH/km

Change of name on certificates to TURCK GmbH

**Annex:**

[BVS\\_23\\_0025X\\_Turck\\_Annex\\_issue2.pdf](#)



# IECEX Certificate of Conformity



**Certificate No.:** IECEX BVS 23.0025X Issue No. 1  
**Annex**  
**Page 1 of 1**

## Parameters

### Electrical data

#### **DC supply circuit**

Supply terminal Pwr + and - Power supply	Type of protection Increased safety Ex eb IIC $U_{\text{nominal}} = 24 \text{ VDC (18...32 VDC)}$ $U_{\text{m}} = 40 \text{ VDC}$
Input current consumption	$I_{\text{nominal}} = 116 \text{ mA}$
Power consumption	$P_{\text{nominal}} = 2.8 \text{ W}$
Maximum Power consumption	$P_{\text{max}} \leq 3.8 \text{ W}$

The DC-supply circuit is safely electrically isolated from earth and from all other circuits.

#### **IS-100BASE-TX Ethernet Interface (Intrinsically safe)**

(only for media converter FOCEN11Ex-2G)

RJ45 socket X300	Type of protection Intrinsic safety Ex ia IIC resp. Ex ia IIIC
Maximum output voltage	$U_{\text{o}} = 4.1 \text{ V}$
Maximum output current	$I_{\text{o}} = 277 \text{ mA}$
Maximum output power	$P_{\text{o}} = 283 \text{ mW}$
Linear output characteristics	
Effective internal capacitance	$C_{\text{i}}$ negligible
Effective internal inductance	$L_{\text{i}}$ negligible

The Ethernet interface may only be connected to devices with an identically designed interface: only to Turck IS-100BASE-TX Ethernet interfaces or interfaces approved by Turck with:

Maximum output voltage	$U_{\text{o}} = 4.1 \text{ V}$
Maximum output current	$I_{\text{o}} = 277 \text{ mA}$
Maximum output power	$P_{\text{o}} = 283 \text{ mW}$

The following values apply to the connection cable:

Maximum cable length	100 m
Cable inductance	$L_{\text{c}} \leq 1.4 \text{ mH/km}$
Cable capacitance	$C_{\text{c}} \leq 52 \text{ nF/km}$

No concentrated external inductances or capacitances are permitted in the Ethernet-System.

The Ethernet interfaces are safely galvanically isolated from earth and from all other circuits of the media converter.

#### **Optical interface**

Transmitting diode	Type of protection op is
Wavelength	$\lambda_{\text{nominal}} = 1300 \text{ nm}$
Optical power (maximum)	$P_{\text{opt,max}} < 1 \text{ mW}$

#### **Ethernet interface**

(only for media converter FOCEN11-3G)

RJ45 socket X300	Type of protection increased safety ec IIC
Signal amplitude Output signal	$U_{\text{nominal}} = 3.3 \text{ V}$ $U_{\text{nominal,differential}} = 1.0 \text{ V}$
Signal amplitude Input signal	$U_{\text{nominal}} = 3.3 \text{ V}$ $U_{\text{nominal,differential}} = 1.0 \text{ V}$ $U_{\text{m}} = 40 \text{ V}$

### Thermal data

Permissible temperature range at the place of installation of the media converter:  $T_{\text{a}}: -40 \text{ }^{\circ}\text{C} \dots 70 \text{ }^{\circ}\text{C}$